

# WIRED TRANSMISSION DIGITAL TORQUE SCREWDRIVERS (KEYBOARD SIGNAL)







## Torque screwdrivers:

- Clockwise and counter-clockwise operation
- Unit: cN.m, in.lb, kg.cm
- Peak and track working modes
- Target torque value can be set, with audible and visible alarm:
  - Green LED light on and buzzer sounds when target torque value is 90%~100% of target torque
  - Red and green LED lights on and buzzer sounds when target torque value is reached
- Auto power off

# Data transmission:

■ Keyboard signal through a cable, can be transmitted to Excel, Word, Txt, etc

### **SPECIFICATION**

of Edition Total						
Part No.		IST-2SD50	IST-2SD200	IST-2SD400	IST-2SD600	
Range		0.88~4.42in. <b>l</b> b	3.54~17.70in. <b>l</b> b	7.08~35.39in. <b>l</b> b	10.61~53.09in. <b>l</b> b	
Accuracy	clockwise	±2%				
	counter-clockwise	±3%				
Resolution		0.01in.lb				
Size of hex socket (L)		1/4"				
Power supply		1 x 3.7V replaceable lithium battery				
Length		7.99"				
Weight		0.42 <b>l</b> b				



hex screwdriver bits (included)



phillips screwdriver bits (included)

#### STANDARD DELIVERY

Torque screwdriver	1 pc
Phillips screwdriver bits	1 pc
Hex screwdriver bits	1 pc

#### **OPTIONAL ACCESSORY**

Calibration cable	IST-SD-CABLE
Transmission cable	IST-HID-CABLE