

# BLUETOOTH DIGITAL TORQUE SCREWDRIVERS (KEYBOARD SIGNAL)



**BUILT-IN  
BLUETOOTH**

**OPTIONAL ACCURACY:  
CLOCKWISE: ±1%  
COUNTER-CLOCKWISE: ±2%**



**IST-3SD200**

### Torque screwdrivers:

- Clockwise and counter-clockwise operation
- Unit: cN.m, in.lb, kg.cm
- Peak and track working modes
- Target torque value can be set, with audible and visible alarm:
  - Green LED light on and buzzer sounds when target torque value is 90%~100% of target torque
  - Red and green LED lights on and buzzer sounds when target torque value is reached
- Auto power off

### Data transmission:

- Built-in Bluetooth module, which can be connected with computers (with Bluetooth function), mobile phones, tablets and other devices
- Keyboard signal, can be transmitted to Excel
- Transmission distance is 394" (no obstacles, no electromagnetic interference)
- Bluetooth connection and disconnection are respectively shown by indicator lights

### SPECIFICATION

Part No.	IST-3SD50	IST-3SD200	IST-3SD400	IST-3SD600
Range	0.88~4.42in.lb	3.54~17.70in.lb	7.08~35.39in.lb	10.61~53.09in.lb
Accuracy	clockwise	±2%		
	counter-clockwise	±3%		
Resolution	0.01in.lb			
Size of hex socket (L)	1/4"			
Power supply	1 x 3.7V replaceable lithium battery			
Length	7.99"			
Weight	0.42lb			

### STANDARD DELIVERY

Torque screwdriver	1 pc
Phillips screwdriver bits	1 pc
Hex screwdriver bits	1 pc

### OPTIONAL ACCESSORY

Calibration cable	IST-SD-CABLE
-------------------	--------------



hex screwdriver bits  
(included)



Phillips screwdriver  
bits (included)